

## Features

- Direct Filter Toko Replacement
- Shielded
- High Q
- Wide Inductance Range

## Descriptions

These helical filter series are compact tunable RF helical filters to directly replace Toko helical filter series.

### Toko EQUIVALENTS-MCV K2RB Series for Toko 5HW (50Ω)

MCV Part NO.	Toko Part NO.	Fo (MHz)	-3dB B.W. (MHz) min	I.L.(dB) max	Selectivity	
					Fo-50MHz (dB) min	Fo+50MHz (dB) min
K2RB-320M-10M	-----	320M	10M	3	25	25
K2RB-340M-10M	-----	340M	10M	3	25	25
K2RB-365M-10M	5HW-35045A-365	365M	10M	3.5	25	25
K2RB-380M-10M	5HW-36535A-380	380M	10M	3.5	25	25
K2RB-415M-10M	-----	415M	10M	3.5	25	25
K2RB-425M-10M	5HW-39545A-425	425M	10M	3.5	25	25
K2RB-430M-10M	5HW-40545A-430	430M	10M	3.5	25	25
K2RB-450M-11M	5HW-40545A-450	450M	11M	3.5	22	25
K2RB-474M-11M	5HW-44545A-474	474M	11M	3.5	22	25
K2RB-475M-11M	5HW-44545A-475	475M	11M	3.5	22	25
K2RB-505M-14M	5HW-47535A-505	505M	14M	3.5	20	25
K2RB-530M-14M	5HW-51035A-530	530M	14M	3.5	20	24
K2RB-545M-14M	5HW-52535A-545	545M	14M	3.5	20	24
K2RB-625M-14M	5HW-58080A-625	625M	14M	3	20	16
K2RB-670M-20M	5HW-65535A-670	670M	20M	3	30(100)	25(100)
K2RB-700M-20M	5HW-68050A-700	700M	20M	3	50(100)	30(100)
K2RB-735M-20M	5HW-73050A-735	735M	20M	3	40(100)	30(100)
K2RB-820M-20M	5HW-78045A-820	820M	20M	3.5	35(100)	25(100)
K2RB-862M-21M	-----	862M	21M	3.5	34(100)	26(100)
K2RB-880M-20M	5HW-82560A-880	880M	20M	3.5	36(100)	27(100)
K2RB-914M-25M	5HW-88560A-914	914M	25M	3	30(100)	23(100)
K2RB-959M-25M	5HW-94555A-959	959M	25M	3.5	25(100)	20(100)
K2RB-1010M-26M	5HW-100090A-1010	1010M	26M	3.5	25(100)	20(100)
K2RB-1130M-26M	5HW-109060A-1130	1130M	26M	3.5	25(100)	20(100)
K2RC-1195M-35M	5HW-115045F-1195	1195M	35M	3.5	20(100)	20(100)
K2RC-1225M-35M	5HW-120050F-1225	1225M	35M	3.5	20(100)	20(100)
K2RC-1305M-35M	5HW-125055F-1305	1305M	35M	3	20(100)	18(100)

### Notes:

1. Size: 5.6 x 11.2 x 8.6(L x W x H)mm
2. All Items are available In sample quantity in stock
3. Center frequency can be customized

## Toko EQUIVALENTS-MCV K3RFT Series for Toko 5HT (50Ω)

MCV Part NO.	Toko Part NO.	Fo (MHz)	-3dB B.W. (MHz) min	I.L.(dB) max	Selectivity	
					Fo-50MHz (dB) min	Fo+50MHz (dB) min
K3RFT-320M-20M	-----	320M	20M	3.5	33	25
K3RFT-340M-20M	-----	340M	20M	3.5	33	25
K3RFT-360M-20M	5HT-36020AS-360	360M	20M	4	33	25
K3RFT-370M-20M	-----	370M	20M	4	33	25
K3RFT-380M-20M	5HT-38020AS-380	380M	20M	4	28	24
K3RFT-390M-20M	-----	390M	20M	4	28	24
K3RFT-400M-15M	5HT-40020AS-400	400M	15M	4	34	31
K3RFT-410M-16M	-----	410M	16M	4	34	30
K3RFT-410.7M-10M	5HT-410.750AS-410.7	410.7	10M	4.5	48	44
K3RFT-420M-16M	5HT-42020AS-420	420M	16M	4	55	27
K3RFT-430M-18M	-----	430M	18M	4	52	31
K3RFT-435M-10M	5HT-43510AS-435	435M	10M	4.5	32	30
K3RFT-440M-18M	5HT-44020AS-440	440M	18M	4	28	25
K3RFT-450M-18M	-----	450M	18M	4	28	25
K3RFT-460M-18M	5HT-46020AS-460	460M	18M	4	28	23
K3RFT-480M-18M	5HT-48030AS-480	480M	18M	4	26	22
K3RFT-495M-20M	5HT-49520AS-495	495M	20M	4	26	22
K3RFT-515M-20M	5HT-51535AS-515	515M	20M	4	25	20
K3RFT-518M-40M	5HT-51820AS-518	518M	40M	4	20	17
K3RBT-520M-14M	5HT-52070AS-520	520M	14M	4	25	22
K3RBT-590M-18M	5HT-59065F-590	590M	18M	4	34	25
K3RBT-635M-18M	5HT-63540F-635	635M	18M	4	30	26
K3RBT-655M-16M	5HT-65550F-655	655M	16M	4	30	26
K3RBT-705M-20M	5HT-70530F-705	705M	20M	4	30	26
K3RBT-735M-20M	5HT-73565F-735	735M	20M	4	28	24
K3RBT-800M-20M	5HT-80030F-800	800M	20M	4	28	24
K3RBT-830M-20M	5HT-83050F-830	830M	20M	4	26	22
K3RBT-862M-20M	5HT-86220F-880	862M	20M	4	24	20
K3RBT-880M-20M	5HT-88065F-880	880M	20M	4	24	20
K3RBT-945M-20M	5HT-94535F-945	945M	20M	4	22	18
K3RBT-980M-20M	5HT-98030F-980	980M	20M	4	22	18
K3RBT-1010M-20M	5HT-101045F-1010	1010M	20M	4	18	14
K3RBT-1055M-20M	5HT-105535F-1055	1055M	20M	4	18	14
K3RBT-1090M-20M	5HT-109065F-1090	1090M	20M	4	17	15
K3RCT3-1125M-20M	5HT-112570C-1125	1125M	20M	4.5	20	18
K3RCT3-1230M-20M	5HT-123080C-1230	1230M	20M	4.5	20	16

**Notes:**

1. Size: 5.6 x 16.8 x 8.6(L x W x H)mm
2. All Items are available In sample quantity in stock
3. Center frequency can be customized

## Toko EQUIVALENTS-MCV K2B/K2C Series for Toko 7HW (50Ω)

MCV Part NO.	Toko Part NO.	Fo (MHz)	-3dB B.W. (MHz) min	I.L.(dB) max	Selectivity	
					Fo-50MHz (dB) min	Fo+50MHz (dB) min
K2B1-360M-10M	7HW-35515A-360	360M	10	2.5	35	25
K2B1-370M-10M	7HW-36020A-370	370M	10	2.5	35	25
K2B-380M-10M	----	380M	10	2	30	20
K2B1-380M-10M	7HW-37020A-380	380M	10	2.5	35	25
K2B1-390M-10M	7HW-38025A-390	390M	10	2.5	35	25
K2B-400M-10M	----	400M	10	2	30	20
K2B1-410M-10M	7HW-39525A-410	410M	10	2.5	30	20
K2B-420M-10M	----	420M	10	2.5	35	25
K2B1-420M-11M	7HW-40525A-420	420M	11	2.5	30	20
K2B1-435M-11M	7HW-42025A-435	435M	11	2.5	30	20
K2B-440M-10M	----	440M	10	2	30	20
K2B1-450M-11M	7HW-43525A-450	450M	11	2.5	30	20
K2B-460M-10M	----	460M	10	2	30	20
K2B1-460M-11M	7HW-45025A-460	460M	11	2.5	25	20
K2B1-475M-11M	7HW-46025A-475	475M	11	2.5	25	20
K2B-480M-10M	----	480M	10	2	30	20
K2B1-490M-13M	7HW-47530A-490	490M	13	2.5	20	20
K2B-500M-10M	----	500M	10	2	30	20
K2B1-505M-13M	7HW-49030A-505	505M	13	2.5	25	20
K2B-520M-10M	----	520M	10	2	30	20
K2B1-525M-13M	7HW-51030A-525	525M	13	2.5	25	20
K2B-380M-21M	7HW-252MXPR-2252A	380M	21	3.5	(Fo-90)40	(Fo+90)27
K2B-415M-30M	7HW-252MXPR-2443A	415M	30	5	(Fo-30)8	(Fo+30)7
K2B1-405M-15M	7HW-252MXPR-2535A	405M	15	3.5	(Fo-30)15	(Fo+30)13
K2B-405M-20M	----	405M	20	2	(Fo-50)22	(Fo+50)16
K2B1-420M-11M	7HW-252MXPR-2536A	420M	11	3.5	(Fo-30)15	(Fo+30)13
K2B1-435M-11M	7HW-252MXPR-2537A	435M	11	3.5	(Fo-30)15	(Fo+30)13
K2B-435M-20M	----	435M	20	2	(Fo-50)22	(Fo+50)16
K2B-453M-20M	7HW-252MXPR-2767A	453M	20	2	(Fo-50)25	(Fo+50)17
K2B-462M-20M	7HW-252MXPR-2689A	462M	20	2	(Fo-50)22	(Fo+50)16
K2B-480M-20M	7HW-252MXPR-2765A	480M	20	2	(Fo-50)22	(Fo+50)16
K2C-600M-15M	7HW-252HXPK-2733F	600M	15	3	(Fo-30)20	(Fo+30)15
K2C-640M-15M	7HW-252HXPK-2708F	640M	15	3	(Fo-30)18	(Fo+30)15
K2C-680M-18M	7HW-252HXPK-2701F	680M	18	3	(Fo-30)16	(Fo+30)13
K2C-785M-20M	7HW-252HXPK-2787F	785M	20	2.5	(Fo-30)13	(Fo+30)10
K2C-870M-25M	7HW-252HXPK-2770F	870M	25	2.5	(Fo-30)8	(Fo+30)7

**Notes:**

1. Size: 7.6 x 15.3 x 13(L x W x H)mm
2. All Items are available In sample quantity in stock
3. Center frequency can be customized

## Toko EQUIVALENTS-MCV K3BT/K3CT Series for Toko 7HT (50Ω)

MCV Part NO.	Toko Part NO.	Fo (MHz)	-3dB B.W. (MHz) min	I.L.(dB) max	Selectivity	
					Fo-50MHz (dB) min	Fo+50MHz (dB) min
K3BT-370M-10M	7HT-302MXPR-1138D*	370M	10	3.5	40	35
K3BT-370M-16M	7HT-302MXPR-1138D	370M	16	3	40	35
K3BT-390M-10M	7HT-302MXPR-1137D*	390M	10	3.5	40	35
K3BT-390M-16M	7HT-302MXPR-1137D	390M	16	3	40	30
K3BT-410M-11M	7HT-302MXPR-1136D*	410M	11	3.5	40	35
K3BT-410M-16M	7HT-302MXPR-1136D	410M	16	3	40	30
K3BT-415M-16M	7HT-302MXPR-1109D	415M	16	3	40	30
K3BT-465M-15M	7HT-302MXPR-1110D	465M	15	3	40	30
K3BT-500M-16M	7HT-302MXPR-1108D	500M	16	3	35	30
K3BT-680M-13M	7HT-302MXPR-1119D	680M	13	3.5	40	30
K3CT1-833M-16M	7HT-302HXPK-1111B	883M	16	3.5	30	25
K3CT1-833M-21M	7HT-302HXPK-1111B	883M	21	3	30	20
K3BT-415M-20M	7HT-302MXP-688D	415M	20	3	36	26
K3BT-425M-20M	7HT-302MXP-689D	425M	20	3	36	26
K3BT-435M-20M	7HT-302MXP-690D	435M	20	3	36	26
K3BT-455M-20M	7HT-302MXP-691D	455M	20	3	36	26
K3B-485M-20M	7HT-302MXP-677A	485M	20	2.5	20	18
K3BT-510M-15M	7HT-302MXP-667D	510M	15	3.5	(Fo-40)30	(Fo+40)23
K3CT2-600M-20M	7HT-302MXP-606E	600M	20	3.5	(Fo-30)16	(Fo+30)11
K3BT-612M-18M	7HT-302HN-528D	612M	18	3.5	(Fo-30)20	(Fo+30)14
K3CT2-651M-10M	7HT-302HN-565E	651M	10	4.5	(Fo-50)40	(Fo+50)40
K3BT-835M-20M	7HT-302HN-051D	835M	20	3	(Fo-50)40	(Fo+50)26
K3CT1-860.5M-23M	7HT-302HN-589B	860.5M	23	3.5	(Fo-80)47	(Fo+80)35
K3BT-880M-25M	7HT-302HN-052D	880M	25	3	(Fo-40)20	(Fo+40)15
K3CT1-904M-12M	7HT-302HA-018B	904M	12	4	(Fo-60)40	(Fo+60)30
K3CT1-904M-20M	7HT-302HA-018B	904M	20	3.5	(Fo-60)35	(Fo+60)28
K3CT1-915M-12M	7HT-302HN-487B	915M	12	5	(Fo-90)48	(Fo+90)40
K3CT1-938M-15M	7HT-302HN-529B	938M	15	5	(Fo-30)23	(Fo+30)19
K3CT1-947M-18M	7HT-302HN-493B	947M	18	4.5	(Fo-50)32	(Fo+50)25
K3CT1-960M-12M	7HT-302HN-486B	960M	12	5	(Fo-90)55	(Fo+90)45
K3CT1-1015M-25M	7HT-302HN-071B	1015M	25	4	(Fo-40)20	(Fo+40)16

**Notes:**

1. Size: 7.6 x 22.9 x 13(L x W x H)mm
2. All Items are available In sample quantity in stock
3. Center frequency can be customized

## Toko EQUIVALENTS-MCV TDW/TTW/TDW Series for Toko 5CHW/5CHT/5CHLW (50Ω)

MCV Part NO.	Toko Part NO.	Fo (MHz)	-1dB B.W. (MHz) min	I.L.(dB) max	Selectivity	
					Fo-50MHz (dB) min	Fo+50MHz (dB) min
TDW2896A-(401-450M)	5CHW-492S-1051A	420	>10M	2.5	17	25
TDW2896A-(401-450M)	5CHW-492S-1052A	425	>10M	2.5	17	25
TDW2896A-(401-450M)	5CHW-492S-1053A	427	>10M	2.5	17	25
TDW2896A-(401-450M)	5CHW-492S-1054A	430	>10M	2.5	17	25
TDW2896A-(401-450M)	5CHW-492S-1055A	435	>10M	2.5	17	25
TDW2896A-(401-450M)	5CHW-492S-1056A	440	>10M	2.5	17	25
TDW2896A-(401-450M)	5CHW-492S-1057A	450	>10M	2.5	17	25
TDW2897A-(451-500M)	5CHW-492S-1058A	452	>10M	2.5	15	23
TDW2897A-(451-500M)	5CHW-492S-1059A	456	>10M	2.5	15	23
TDW2897A-(451-500M)	5CHW-492S-1060A	460	>10M	2.5	15	23
TDW2897A-(451-500M)	5CHW-492S-1061A	463.5	>10M	2.5	15	23
TDW2897A-(451-500M)	5CHW-492S-1062A	465	>10M	2.5	15	23
TDW2897A-(451-500M)	5CHW-492S-1063A	470	>10M	2.5	15	23
TDW2897A-(451-500M)	5CHW-492S-1064A	480	>10M	2.5	15	23
TDW2898A-(501-550M)	5CHW-492S-1065A	510	>10M	2.5	14	23
TTW3895A-395M	5CHT-493S-1066A	395	>10M	3.5	38	35
TTW3433A-420M	5CHT-493S-1067A	420	>10M	3.5	44	34
TTW3896A(401-450M)	5CHT-493S-1068A	425	>10M	3.5	33	30
TTW3896A(401-450M)	5CHT-493S-1069A	430	>10M	3.5	33	30
TTW3896A(401-450M)	5CHT-493S-1070A	435	>10M	3.5	33	30
TTW3896A(401-450M)	5CHT-493S-1071A	440	>10M	3.5	33	30
TTW3896A(401-450M)	5CHT-493S-1072A	450	>10M	3.5	33	30
TTW3897A-(451-500M)	5CHT-493S-1073A	452	>10M	4.5	51	41
TTW3897A-(451-500M)	5CHT-493S-1074A	456	>10M	4.5	51	41
TTW3897A-(451-500M)	5CHT-493S-1075A	460	>10M	4.5	51	41
TTW3897A-(451-500M)	5CHT-493S-1076A	465	>10M	4.5	51	41
TTW3897A-(451-500M)	5CHT-493S-1077A	470	>10M	4.5	51	41
TTW3897A-(451-500M)	5CHT-493S-1078A	480	>10M	4.5	51	41
TTW3897A-(451-500M)	5CHT-493S-1079A	485	>10M	4.5	51	41
TTW3898A-510M	5CHT-493S-1080A	510	>10M	3.5	33	31
TDW2505B-(800-850M)	5CHLW-477MS-1031A	832.5	25M	3	(Fo-100)25	(Fo+100)18
TDW2505B-(800-850M)	5CHLW-477MS-1032A	850	25M	3	(Fo-100)25	(Fo+100)18
TDW2505B-(800-850M)	5CHLW-477MS-1093A	836.5	25M	3	(Fo-100)25	(Fo+100)18
TDW2700B-(851-900M)	5CHLW-477MS-1033A	870	25M	2.5	(Fo-100)25	(Fo+100)18
TDW2700B-(851-900M)	5CHLW-477MS-1094A	881.5	25M	2.5	(Fo-100)25	(Fo+100)18
TDW2701B-(901-950M)	5CHLW-477MS-1034A	902.5	25M	2.5	(Fo-100)25	(Fo+100)18
TDW2701B-(901-950M)	5CHLW-477MS-1035A	915	25M	2.5	(Fo-100)25	(Fo+100)18
TDW2701B-(901-950M)	5CHLW-477MS-1036A	933	25M	2.5	(Fo-100)25	(Fo+100)18
TDW2701B-(901-950M)	5CHLW-477MS-1037A	947.5	25M	2.5	(Fo-100)25	(Fo+100)18
TDW2701B-(901-950M)	5CHLW-477MS-1038A	950	25M	2.5	(Fo-100)25	(Fo+100)18

**Notes:**

1. TOKO's Selectivity is dB, MCV is dBc.
2. We are replacing TOKO filter SMD type with Pin type MCV filter.
3. Center frequency can be customized

## Toko EQUIVALENTS-MCV TF Series for Toko CBT13 (50Ω)

MCV Part NO.	Toko Part NO.	Fo (MHz)	-1 or -3dB B.W. (MHz) min	I.L.(dB) max	Selectivity	
					Fo-( )MHz (dB) min	Fo+( )MHz (dB) min
TF69280A1-100M-6M	CBT13-272MT-1173A	100	4.0(-3BW)	4	30(15)	30(15)
TF69280A1-107M-6M	CBT13-272MT-1230D	107	3.0(-3BW)	4.5	33(10)	22(15)
TF69198B1-110M-6M	CBT13-272MT-1180A	110	3.0(-3BW)	5.5	37(10)	30(10)
TF69198B1-124M-6M	CBT13-272MT-1177D	124	3.5(-3BW)	3.5	21(6)	17(6)
TF69676B1-130M-6M	CBT13-272MT-1175D	130	3.0(-3BW)	5.5	21(5)	18(5)
TF69676B1-133.7M-6M	CBT13-272MT-1176D	133.7	3.5(-3BW)	3.5	23(6)	18(6)
TF69205B1-134M-8M	CBT13-272MT-1116A	134	5.0(-1BW)	3	24(15)	24(15)
TF6955B1-137.5M-6M	CBT13-272MT-1169D	137.5	2.0(-1BW)	4.5	35(10)	30(10)
TF6957B1-140.2M-7M	CBT13-272MT-1117D	140.21	3.7(-1BW)	3	26(10)	25(10)
TF6957B1-143M-7M	CBT13-272MT-1119D	143	3.0(-1BW)	4	35(10)	22(10)
TF6955B1-145M-6M	CBT13-272MT-1006A	145	2.8(-3BW)	8	25(6)	25(6)
TF6955B1-145M-6M	CBT13-272MT-1008A	145	1.2(-3BW)	8	30(6)	30(6)
TF69709B-147M-5M	CBT13-272MT-1181D	147	4.0(-3BW)	3.5	20(6)	15(6)
TF6914B-156.7M-3M	CBT13-272MT-1219A	156.7	1.5(-3BW)	7	33(6)	25(6)
TF69709B-157M-5M	CBT13-272MT-1124D	157	3.5(-3BW)	3.5	17(6)	13(6)
TF69711B-159M-7M	CBT13-272MT-1174A	159	7.0(-3BW)	3	35(20)	33(20)
TF6914B-160M-3M	CBT13-272MT-1123A	160	2.0(-3BW)	6	17(6)	15(5)
TF6914B-161M-3M	CBT13-272MT-1221A	161	2.2(-1BW)	4.5	32(10)	40(10)
TF6914B-161.3M-3M	CBT13-272MT-1218A	161.3	1.5(-3BW)	7	30(6)	25(6)
TF6914B-164M-3M	CBT13-272MT-1148A	164	1.0(-3BW)	8.5	30(5)	25(5)
TF6959D-165M-7M	CBT13-272MT-1118D	165	3.9(-1BW)	3	15(10)	16(10)
TF6959D-169M-7M	CBT13-272MT-1120A	169	3.5(-3BW)	6	35(10)	25(10)
TF6959D-171M-7M	CBT13-272MT-1125D	171	4.4(-1BW)	2.5	16(10)	14(10)
TF6959D-177M-7M	CBT13-272MT-1126F	177	4.0(-1BW)	3	15(10)	13(10)
TF6959D-183M-7M	CBT13-272MT-1127F	183	4.0(-1BW)	3	17(10)	17(10)
TF6959D-185M-7M	CBT13-272MT-1131A	185	3.0(-3BW)	5	24(6)	20(6)
TF6959D-189M-7M	CBT13-272MT-1128F	189	4.0(-1BW)	3.5	19(10)	18(10)
TF6959D-194.5M-7M	CBT13-272MT-1208A	194.5	3.0(-3BW)	4.5	40(15)	35(15)
TF6959D-195M-7M	CBT13-272MT-1129F	195	4.2(-1BW)	3	18(10)	18(10)
TF8929B1-196M-5M	CBT13-272MT-1182A	196	3.0(-3BW)	5	32(10)	25(10)
TF8929B1-200M-5M	CBT13-272MT-1195A	200	3.0(-3BW)	7	19(6)	17(6)
TF8929B1-201M-5M	CBT13-272MT-1130F	201	4.5(-1BW)	3	16(10)	16(10)
TF8929B1-215M-5M	CBT13-272MT-1132A	215	4.0(-3BW)	4	15(6)	14(6)
TF8929B1-220M-5M	CBT13-272MT-1209A	220	5.0(-3BW)	3	40(15)	30(15)
TF8929B1-223M-5M	CBT13-272MT-1146A	223	4.0(-3BW)	5	24(10)	18(10)
TF8929B1-226.4M-5M	CBT13-272MT-1188A	226.4	2.5(-1BW)	6	32(10)	25(10)
TF6958B-170M-4M	CBT13-272MT-1013A	170	1.5(-3BW)	8	25(6)	25(6)
TF6958B-170M-4M	CBT13-272MT-1007A	170	1.0(-1BW)	9	31(5)	30(5)
TF8929B1-223M-5M	CBT13-272MT-1080A	223	2.6(-1BW)	6	28(10)	40(20)
TF69185B-230M-17M	CBT13-272MT-1413A	230	12.5(-3BW)	2	18(20)	15(20)

**Notes:**

1. All Items are available In sample quantity in stock
2. Center frequency can be customized



## Toko EQUIVALENTS-MCV TT Series for Toko CBW13 (50Ω)

MCV Part NO.	Toko Part NO.	Fo (MHz)	-1dB B.W. (MHz) min	I.L.(dB) max	Selectivity	
					Fo-50MHz (dB) min	Fo+50MHz (dB) min
TT67280A1-(96~107M)-4M	CBW13-271MT-1149A	99	3.0	3.0	30	20
TT67280A1-(96~107M)-4M	CBW13-271MT-1150A	103	3.0	2.5	30	20
TT67198B1-(107~125M)-4M	CBW13-271MT-1151A	107.5	3.0	2.5	30	20
TT67198B1-(107~125M)-4M	CBW13-271MT-1152A	111	3.0	2.5	30	20
TT67198B1-(107~125M)-4M	CBW13-271MT-1153A	115	2.0	2.5	32	22
TT67198B1-(107~125M)-4M	CBW13-271MT-1154A	119	2.5	2.0	30	22
TT67198B1-(107~125M)-4M	CBW13-271MT-1155A	122	2.0	2.5	29	27
TT67676B1-(126~145M)-4M	CBW13-271MT-1156A	126	3.0	2.5	25	24
TT67676B1-(126~145M)-4M	CBW13-271MT-1157A	131	2.0	2.5	24	23
TT67676B1-(126~145M)-4M	CBW13-271MT-1158A	138	2.5	2.5	28	24
TT67709B-(146~165M)-4M	CBW13-271MT-1159A	146	2.5	2.5	27	23
TT67709B-(146~165M)-4M	CBW13-271MT-1160A	154	2.5	2.5	25	21
TT67709B-(146~165M)-4M	CBW13-271MT-1161A	164	2.5	3.0	28	25
TT6786B-(166~195M)-4M	CBW13-271MT-1162A	171	2.5	2.5	20	18
TT6786B-(166~195M)-4M	CBW13-271MT-1163A	182.5	3.0	3.0	23	20
TT6760B-(196~220M)-4M	CBW13-271MT-1164A	194.5	2.5	3.0	27	24
TT6760B-(196~220M)-4M	CBW13-271MT-1165A	207.5	2.5	3.0	26	23
TT6760B-(196~220M)-4 M	CBW13-271MT-1166A	220	2.0	3.0	20	18

**Notes:**

1. All Items are available In sample quantity in stock
2. Center frequency can be customized